

Initial Commands

colored CLI	set cli mode -color ON
User / Host / Time	set cli prompt %u@%h-%T

Show Basic Settings

Firmware Version	show version
Hostname	show hostname
Hardware Details	show hardware
Interfaces	show interface - summary
SSL Summary	stat ssl
HA node configuration	show node

NetScaler Configuration Info

Show IPs	show ip
Features	show feature
HA Modes	show ns mode
All Infos	show info
License Information	show license
Running Configuration	show run more

Show Load Balancing

Show VServer	show lb vserver <name>
Show All VServers	show lb vserver more
Show Service	show service <srv>
Show Service Group	show servicegroup <svgrp>
Show Monitor	show monitor <mon>
Show Persistent Sessions	show persistentssions

Troubleshoot AAA Problems

to monitor all authentication process:
 shell
 cat /tmp/aaa.debug

Create LoadBalancing StoreFront

StoreFront Monitor

```
add lb monitor <StoreFront>
STOREFRONT -scriptName nssf.pl -dispatcherIP 127.0.0.1 -dispatcherPort 3013 -secure YES -storename <Store>
```

Add StoreFront Server

```
add server <SF01> <IP1>
add server <SF02> <IP2>
```

Create Service Group

```
add serviceGroup svcgrp-StoreFront-SSL
SSL -maxClient 0 -maxReq 0 -cip
ENABLED X-Forwarded-For
bind serviceGroup svcgrp-StoreFront-SSL
<SF01> 443
bind serviceGroup svcgrp-StoreFront-SSL
<SF02> 443
bind serviceGroup svcgrp-StoreFront-SSL -
monitorName <StoreFront>
```

Create VServer

```
add lb vserver <lbvip-StoreFront-SSL> SSL
10.2.2.221 443 -persistenceType
SOURCEIP -timeout 60
bind lb vserver lbvip-StoreFront-SSL <sv-
cgrp-StoreFront-SSL>
bind ssl vserver <lbvip-StoreFront-SSL> -
certkeyName <WildCorpCom>
set ssl vserver <lbvip-StoreFront-SSL> -
sslRedirect ENABLED -ssl3 DISABLED
```



By kevinkleist

cheatography.com/kevinkleist/

Not published yet.

Last updated 16th October, 2017.

Page 1 of 1.

Sponsored by **Readable.com**

Measure your website readability!

<https://readable.com>